



ESD Handbook TR20.20 Table 1 lists under Typical Static Electricity Sources "Brushes (camel/pig hair and synthetic bristles)." "It should be understood that any object, item, material or person could be a source of static electricity in the work environment. Removal of unnecessary nonconductors, replacing nonconductive materials with dissipative or conductive materials and grounding all conductors are the principle methods of controlling static electricity in the workplace, regardless of the activity." (TR 20.20 section 2.4)

Features:

- ESD Brushes are ideal for removing dust, dirt and left over materials from printed circuit boards (PCB) and other static sensitive components
- Brushes minimize static charge generation and remove electrostatic charges to ground when held by grounded personnel
- Volume Resistance of Conductive Fibers:
 1×10^3 to $< 1 \times 10^4$ ohms tested per ANSI/ESD STM 11.12
- Bristle Material: Natural hair bristles with conductive black fibers
- Bristle Firmness: Soft
- Length 6" (152mm)
- Brush Width: 1/4" (6mm)
- Handle Material: Conductive black polypropylene

Made in Israel

Unless otherwise noted, tolerance is $\pm 10\%$.

Specifications and procedures subject to change without notice.

ESD BRUSH, CONDUCTIVE, ROUND HANDLE, BEIGE SOFT BRISTLES, 1/4 IN

3651 WALNUT AVE., CHINO, CA 91710
PHONE: (909) 627-2453
WEBSITE: MendaPump.com

**DRAWING
NUMBER**
36091

DATE:
December
2017

MENDA